



Procedure: To perform a cold reset on printers without resetting the IP address.

Printers: All HP LaserJet printers with embedded LAN that use the (✓) or (OK) as the select button.

Step 1

- With the printer off, turn on and wait until the memory count begins, then press and hold the (✓) (OK) button until the three control panel lights light solid then release.
- Printer should then display "SELECT LANGUAGE".
- Use the (↑) or (↓) buttons until "EMBEDDED LAN DISABLE" appears highlighted and press (✓)(OK) .
- Let the printer return to "READY".

Step 2

- With the printer off, turn on and wait until the memory count begins, then press and hold the (✓)(OK) button until the three control panel Lights light solid then release.
- Printer should then display "SELECT LANGUAGE".
- Use the (↑) or (↓) buttons until "COLD RESET" appears highlighted and press (✓)(OK).
- Let the printer return to "READY".

Step 3

- With the printer off, turn on and wait until the memory count begins, then press and hold the (✓)(OK) button until the three control panel Lights light solid then release.
- Printer should then display "SELECT LANGUAGE".
- Use the (↑) or (↓) buttons until "EMBEDDED LAN ENABLE" appears highlighted and press (✓)(OK).
- Let the printer return to "READY".

Note: HP MFP printers use the 3, 9, and 6 buttons in place of (↑),(↓), and (✓). For more information, please contact Tech Support.